



FS1540

Transducer ceiling for brightness or movement, digital output

Measuring size: brightness, motion

Output: Modbus RTU, Relay

Highlights: in the false ceiling by 2 tension springs



Description

The transducer FS1540 detects the brightness or movement and converts the measured values into a digital output signal.

The unobtrusive housing with a clip fastening and reverse polarity protected socket is suitable for the quick assembly in intermediate ceilings. The brightness sensor is optimally suited for an energy efficient control of buildings, such as e.g. controlling the lighting in offices, industrial facilities etc..

In the register the switching threshold, hysteresis, offset value etc can be specified.

As special equipment a potential-free alternating contact is available. The optional alternating contact can be configured for measured values from other bus-participants.

The configuration of address, transmission mode/speed, terminating resistor and master/slave function of the bus-devices can easily be done using the innovative DIP switch technology. Thus devices can quickly and easily be integrated into the system and later parameterised via the master.

The bus-devices can even be reset to the works settings during operation of the master. Thus the basic functionality of the device is recreated in a matter of seconds. This can be necessary in the event of incorrect parameterisations of, e.g. offset, switching threshold, display modes etc..

By means of the FS master/slave topology autarkic nodes without additional SPS master can be installed within the device series. Hereby a bus-device assumes the master function in the node. This requests the measured values from other bus-participants, automatically enters these into the corresponding register and shows them in the internal display. Furthermore the master can evaluate and operate additional actuators in the device series (analogue in- and outputs, relay station).



Technical Specifications

Measurement range brightness	0-100 kLux
Measurement range motion	motion yes/no, apex angle 90°/110° on 360° range, reach 10 m
Accuracy brightness	±10% FS
Temperature dependency	±5% FS / 10 K
Response time (t90)	< 1 s
Offset	can be entered in the register
Sensor	Motion: infrared sensor, Brightness: photodiode
Sensor protection	mounted inside housing
Supply voltage	24 V DC (±5%)
Current consumption	max. 20-200 mA, depending on the selected measurand and equipment
Digital output	Modbus RTU
Alarm output	1 x potential-free change-over contact, 48 V, 1 A
Switching Hysteresis Relay	can be entered in the register
Holding time	adjustable from 5 s up to 15 min
Threshold	threshold can be entered in the register
Electrical connection	push-in terminal, no tools required, time-saving
Cable	1 m PVC cable
Housing	Sensor: aluminium, colour signal white like RAL 9003, Electronic: polycarbonate PC UL 94 V0 with hinge locks, color signal white similar to RAL 9003
Cable gland	PG11 high-strength cable gland with strain relief
Dimensions	Housing: L 89 x W 80 x H 47 mm
Protection type	Housing/electronic: IP65, Sensor: IP30
Protection class	III
Working range r.H.	0...98% r.H. in contaminant-free, non-condensing air
Working temperature	Electronic: -20...+50°C
Storage temperature	-20...+50°C
Installation	in the false ceiling by 2 tension springs
Approvals	CE, EAC, RoHS



Variants

Article Number			
Brightness	Movement	Output	Equipment
FS1540-MBR-B1-D			
0-100 kLux	-	Modbus RTU	Display
FS1540-MBR-B1-DR			
0-100 kLux	-	Modbus RTU	Display, Relay
FS1540-MBR-B1-R			
0-100 kLux	-	Modbus RTU	Relay
FS1540-MBR-B1-X			
0-100 kLux	-	Modbus RTU	-
FS1540-MBR-M1-D			
-	yes/no	Modbus RTU	Display
FS1540-MBR-M1-DR			
-	yes/no	Modbus RTU	Display, Relay
FS1540-MBR-M1-R			
-	yes/no	Modbus RTU	Relay
FS1540-MBR-M1-X			
-	yes/no	Modbus RTU	-



Dimensional Drawing

